

# AXON

## LED ICAO Triple Line Taxiway Centerline Light

Uni and Bidirectional Inset, 8-inch and 12-inch



ADB SAFEGATE  
**AXON**

### Compliance with Standards

**ICAO** Annex 14, Volume 1

**IEC** 61827

CE

### Uses

#### ICAO

- Triple line taxiway centerline light

### Features and Benefits

#### Efficiency

- EQ has an integrated ILCMS remote for use with the LINC 360 system providing high data capacity and resisting degradation from various types of radio effects to provide a superior communication platform
- Precision aimed optics enhancing photometric performance and complementing extended LED life
- Reduced bottom pan profile allowing for very shallow base can installation
- LED pulse width modulated (PWM) at 400 Hz optimizing LED performance and eliminating perceptible flicker to a moving human observer throughout the range of brightness steps
- Operates at all steps of constant current regulator technologies designed in compliance with IEC or FAA requirements
- Fully dimmable lights, conforming to the dimming curve of traditional halogen lights
- Low protrusion, high-intensity, Style 3 ( $\leq 6.35$  mm) inset light fixtures
- No negative slope in front of the prisms

### Sustainability

- Fully encapsulated all-in-one universal power supplies for Runway, Taxiway, Approach and Omni inset families
- Latest generation LEDs providing a long-lasting light source with high efficiency and low power consumption
- Reinforced top cover substantially exceeding standards to improve durability and longevity (directional beams only)
- One single family of fixtures covering all runway, taxiway and approach applications
- IP68 rated enclosure designed for harsh environments; all fastenings are stainless steel
- Reinforced prism available as an option
- Compatible with existing infrastructure allowing for direct replacement of existing LED inset fixtures

### Safety

- Improved mechanical design to strengthen and consolidate components, improving the customer maintenance experience
- Fail-open option for compatibility with legacy monitoring systems and optimization of advanced control and monitoring systems
- Failed LED Detection as required by Engineering Brief 67D
- Robust lightning protection complying with ANSI/IEEE C62.41-1991; Location Category C2 as required by FAA Engineering Brief 67 Category C2 is defined as a 1.2/50  $\mu$ S – 8/20  $\mu$ S combination wave, with a peak voltage of 10,000 V and a peak current of 5,000 A

## Ordering Code

	Application	Standard(s)	Market Specific	Dimensions	Prism	Beam Orientation	Toe-in	Color - Side 1 (Left)	Color - Side 1 (Left)	Power and Monitoring	Connector and Cable <sup>6</sup>	Options	Version
RS	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

### Application

3C = Curved Beam  
 3N = Narrow Beam  
 3W = Wide Beam

### Standard(s)

4 = Other

### Market Specific

0 = None

### Dimensions

1 = 8 inch (203 mm) diameter, 2 bolt  
 2 = 12 inch (305 mm) diameter, 11.25 inch BC (285 mm)

### Prism

S = Standard prism  
 R = Reinforced prism

### Beam Orientation

1 = Unidirectional  
 2 = Bidirectional

### Toe-in

N = None<sup>2</sup>  
 C = Curved<sup>1,3</sup>  
 L = Left Side Toe-in (Unidirectional)<sup>1,4</sup>  
 R = Right Side Toe-in (Unidirectional)<sup>1,4</sup>

### Color - Side 1 (Left)

F = F-Green (ICAO, default green)  
 B = Blue  
 A = Amber  
 N = None<sup>8</sup>

### Color - Side 1 (Left)

F = F-Green (ICAO, default green)  
 B = Blue  
 A = Amber  
 N = None

### Power and Monitoring

S = 2.8 - 6.6 A, Non-Monitored — Power Only  
 M = 2.8 - 6.6 A, Fail-Open Monitoring  
 R = 2.8 - 6.6 A, EQ Integrated LINC 360<sup>5</sup>

### Connector and Cable<sup>6</sup>

1 = 1 x Style 6 2-Pole Plug, 2 Individual Wires  
 2 = 1 x Style 1 2-Pole Plug, Jacketed SO 2 Core Cable<sup>7</sup>  
 3 = 2 x Style 6 2-Pole Plug, 2 Individual Wires  
 4 = 2 x Style 1 2-Pole Plug, Jacketed SO 2 Core Cable<sup>7</sup>  
 5 = 1 x Flat 3-Pole Plug, 3 Individual Wires  
 6 = 2 x Flat 3-Pole Plug, 3 Individual Wires

### Options

0 = None  
 1 = Arctic Kit

### Version

1 = Version 1

### Ordering Code Notes

1. Left and right side determined by viewing fixture from interior turn radius pavement edge. Side 1 is on your left, side 2 is on your right.
2. 3N and 3W applications.
3. 3C bidirectional application.
4. 3C unidirectional application.
5. EQ light fixtures are only available as a one connector option.
6. All Style 1 corded fixtures will include a ground lug. All Style 6 or 3-pole corded fixtures will be provided with grounding screw(s).
7. SO cord set option is not compatible with shallow bases. If required please contact ADB Safegate.

### Power Supply Options

- Non-monitored — power only
- Monitored — integrated fail-open technology
- EQ with integrated ILCMS with OFDM technology for use with LINC 360 system

### Installation and Maintenance

The light fixture can be installed in a 12-inch or an 8-inch base. Gaskets are sold separately. Refer to the user manual INTEROPERABILITY appendix to identify the correct gasket and bolts for your specific base and ensure a reliable fit.

## Operating Conditions

<b>Operating temperature</b>	-60 °C to +55 °C / -76 °F to +131 °F
<b>Storage temperature</b>	-60 °C to +80 °C / -76 °F to +176 °F
<b>Humidity</b>	Up to 100%

## Dimensions and Weight

<b>Dimensions</b>	203 mm (8 in)	304 mm (12 in)
<b>Weight</b>	2.7 kg / 6.0 lb (8 in)	6.3 kg / 13.9 lb (12 in)

## ANNEX

### 8- and 12-inch light fixtures without Arctic Kit (heater)

Fixture type – 1 cord set <sup>1</sup>	Fixture load	Isolation transformer		CCR load
		Wattage	Load	
Triple line taxiway centerline light, bidirectional, blue/blue	12.5 VA	15 W	7.6 VA	20.1 VA
Triple line taxiway centerline light, bidirectional, amber/amber	14 VA	15 W	7.6 VA	21.6 VA

### 8- and 12-inch light fixtures with Arctic Kit (heater)

Fixture type – 1 cord set <sup>1</sup>	Fixture load	Isolation transformer		CCR load
		Wattage	Load	
Triple line taxiway centerline light				

<sup>1</sup>Values provided are for the "S" option non-monitored power only.

#### Note:

- EQ fixtures:
  - The isolation transformer must have an additional 8 VA available above the fixture load for communication bandwidth. Size transformer to next size up to assure additional 8 VA coverage
  - Legacy BRITE II or AGLAS 2 systems — Order "M" power supply
- Fail-open fixtures:
  - The maximum rating for the isolation transformer is 150 W (a correctly calibrated CCR is important to achieve an accurate fail open response)
- Additional voltage loss not included in the above table which must be factored into the circuit load calculation:
  - Primary cables will result in a higher CCR load
  - Longer secondary cables may result in a larger size isolation transformer requirement
- Efficiency of the isolation transformer depends on the manufacturer of the transformer
- See user manual for the complete power table and cable loss formula. and other power supplies

For more information about the product, including manuals and certifications, please see our Product Center on the ADB SAFEGATE website: [www.adbsafegate.com](http://www.adbsafegate.com).