







BOTTOM VIEW

FISHER & PAYKEL

DATA SHEET

Insert Range Hood, 24"

Model nos:

HP24IDCHX4

(refer page 2 for metrical measurements)

Product Dimensions	in
 Overall height of range hood without ducting adapter 	12 7/16″
Overall height of range hood with ducting adapter	15 11/16″
© Overall width of range hood	20 7/8"
 Overall depth of range hood (excl. cabinetry front panel) 	11"
Diameter of ducting adaptor	6"
© Width of range hood chassis	19 3/8"
⑥ Depth of range hood chassis	10 3/16"
Thickness of flange	1/16"
 Distance from ducting outlet center to rear of chassis 	3 1/4"
 Height adjustability of clip that secures cooker hood (cabinet base panel thickness) 	min 9/16" max 1 9/16"
O Distance from rear to center of light	9 15/16"
① Distance from back of chassis to hard wiring box	8 9/16"
O Distance from center of product to hard wiring box	3 1/4"

Cavity Dimensions Standard Installation	in
Width of cutout	19 11/16"
Depth of cutout	10 1/4"

Minimum distance above cooktops	in
Minimum height from top of cooktop to base of product	24"

Minimum height may be greater if required by your cooktop. Refer to cooktop installation guide for details.

Note: We recommend the cabinet has a door or service panel that can be easily opened to access the power connection.

INDICATES CUTOUT
INDICATES PRODUCT DATUM
INDICATES CABINETRY CLEARANCES

DATE: 23.08.2023	90003053A
------------------	-----------

IMPORTANT NOTE: Throughout this guide, dimensions may vary by $\pm 2mm$ (1/16"). Please read the installation guide for detailed information on installing the product. For full installation instructions & specifications visit fisherpaykel.com





PLAN VIEW





FISHER & PAYKEL

DATA SHEET

Insert Range Hood, 24"

Model nos:

HP24IDCHX4

(refer page 1 for imperial measurements)

Product Dimensions	mm
Overall height of range hood without ducting adapter	316
Overall height of range hood with ducting adapter	398
© Overall width of range hood	530
 Overall depth of rangehood (excl. cabinetry front panel) 	280
© Diameter of ducting adaptor	150
© Width of range hood chassis	492
© Depth of range hood chassis	258
Thickness of flange	2
① Distance from ducting outlet center to rear of chassis	82
 Height adjustability of clip that secures cooker hood (cabinet base panel thickness) 	min 15 max 40
© Distance from rear to center of light	253
© Distance from back of chassis to hard wiring box	217
Distance from center of product to hard wiring box	82

Cavity Dimensions Standard Installation	mm
Width of cutout	500
Depth of cutout	260

Minimum distance above cooktops	mm
Minimum height from top of cooktop to base of product	610

Minimum height may be greater if required by your cooktop. Refer to cooktop installation guide for details.

Note: We recommend the cabinet has a door or service panel that can be easily opened to access the power connection.



BOTTOM VIEW



INDICATES CUTOU	т	
INDICATES PRODU	CT DATUM	
INDICATES CABINI	TRY CLEARANCES	

DATE: 23.08.2023	90003053A
------------------	-----------

IMPORTANT NOTE: Throughout this guide, dimensions may vary by $\pm 2mm$ (1/16"). Please read the installation guide for detailed information on installing the product. For full installation instructions & specifications visit fisherpaykel.com

